

50 High Street, West Mill, 3rd floor, Suite #30 North Andover, MA 01845

Tel: 800-343-1455 Fax: 978-689-9484 or 978-685-6467 E-mail: sales@L-com.com Web: www.L-com.com

# **L-com VGA Video Splitters**

### **■** Product Overview

The LCVS series VGA video splitters are designed to split a single video source to multiple video outputs (monitors). These easy to use VGA splitters are plug-and-play so no software is required for use. Use of a high bandwidth circuit allows high-resolution signals of 350 MHz to be displayed on multiple monitors.

### **■** Features

- Effective transmission distance: 210 feet (65 meters)
- Automatic power save when VGA input is lost
- Cascade option for increased VGA ports

## ■ Part Numbers

| ITEM #  | DESCRIPTION                   |  |
|---------|-------------------------------|--|
| LCVS-12 | 1 X 2 Port VGA Video Splitter |  |
| LCVS-14 | 1 X 4 Port VGA Video Splitter |  |

# **■** Specifications

| ·                        |  |         |  |
|--------------------------|--|---------|--|
|                          | LCVS-12                                      | LCVS-14 |  |
| SVGA Outputs             | 2  | 4       |  |
| Signal Bandwidth         | 350 Mhz                                      |         |  |
| Signal Type              | VGA, SVGA, Multi-Sync                        |         |  |
| Max Distance             | 210 Feet (65 meters)                         |         |  |
| Connector Type - Input   | HD15 Male                                    |         |  |
| Connector Type - Output  | HD15 Female                                  |         |  |
| Power Consumption (Max.) | DC 5V, 200mA- Normal<br>10mA power-save mode |         |  |
| Enclosure                | Metal  |         |  |
| Weight                   | 400g   | 428g    |  |
| Dimensions               | 20 x 85 x 180 (mm)                           |         |  |

## **■** Warranty

We warrant our manufactured products for a period of one year from time of purchase. These products are warranted against defects in workmanship or materials under normal use. We cannot warranty our products in case of misuse, acts of God, or consequential damage. Alteration of product cancels all warranties. Under no circumstances will we be responsible for any damage beyond the replacement cost of the defective merchandise. We reserve the right to repair or replace any products that are returned under warranty.

Tech Support: <u>Techsupport@l-com.com</u> 1-800-343-1455 Outside of the USA Call 1-978-682-6936 www.L-com.com

Copyright © L-com Global Connectivity 2011