



PLUG ASSEMBLY INSTRUCTIONS FOR
Cable with INDIVIDUALLY SHIELDED PAIRS (PIMF or SFTP)
T568B Wiring Pattern

1



Cut cable to length. If you are using a strain relief grommet, slide it over the cable. The larger ends should be facing outward, toward the plug end of the cable.


2



1 to 1 ¼ INCHES


Cut and strip off 1 to 1¼ inches of the outer jacket. Be careful not to cut or nick the braid and foil shields.

3



Pull the braid back over the cable jacket.


4



¼ INCH

Spread out the 4 wire pairs and trim foil to ¼ inch on all 4 pairs.


5



ORANGE PAIR


BROWN PAIR

TAPERED END OF PLASTIC WIRE ALIGNER




OTHER END OF CABLE SHOWING GREEN PAIR IN FRONT

Place plastic wire aligner between the pairs. The tapered end should be toward the braid and jacket. The orange pair will go to the deep channel on the left side and the brown pair will go toward the deep channel on the right. The blue and green pairs will go to the sides that have shallow channels at the middle.


6

END WITH BLUE
PAIR IN FRONT




END WITH GREEN
PAIR IN FRONT

Push the wire aligner down as far as it will go and push pairs into wire aligner channels. Flatten out the wires and arrange the insulation colors so that they match the T568B color map. Keep the red on left and the brown on right. On one end of the cable the blue pair will be towards you, and the green pair will be towards you on the other end.

7


RED ORANGE BLACK BLUE WHITE GREEN YELLOW BROWN

The color pattern shown in these pictures represent the wiring colors used by one manufacturer. Wiring colors may vary by cable. Please verify the color pattern specific to your particular requirements. Shown below is a more typical color scheme.




ORANGE /WHITE ORANGE GREEN /WHITE BLUE BLUE /WHITE GREEN BROWN /WHITE BROWN

When aligning the wires to the color pattern, maintain the existing twist of the wire pairs. Do not add or remove more than $\frac{1}{2}$ twist to any pair to achieve the required color pattern.

8

Trim the ends of the wires to make them even. This will make it easier to insert the wires into the load bar. Remove the least amount of wire necessary to even out the wires.

9

SLOTS

WEDGE

Insert the ends of the wires into the wide end of the load bar, maintaining the wire color sequence. The side with the slots and the wedge shaped end should be facing towards you

10



Bring the loadbar down, tight against the plastic wire aligner. Trim the wires flush to the loadbar.

11




Dress the braid to one side of the jacket.

12




Wrap the braid over the jacket. Press the foil covered pairs fully into the slots in the channels of the plastic wire aligner. Ensure that the foil does not stick out as this makes it difficult to insert this assembly into the plug body.

13




Keep the orange pair to the left and the brown to the right. Push the assembled wires, loadbar, and plastic wire aligner into the plug body subassembly. The plug latch tab should be facing away from you. Firmly push the plug until the wires come in contact with the front inside surface of the plug.

14




Bend the plug shield fingers inward toward the cable. Press the shield fingers as far as they will go. They should easily fit into the Shield Crimp portion of the crimping tool.

15



Insert the un-terminated plug into the crimp tool. Make sure that the plug is fully seated in the tool.


16



Squeeze the handles of the crimp tool together until they are fully depressed, and will open when the handle is released.

Remove the terminated plug from the crimp tool.

17



If used, align the strain relief grommet and push it over the terminated plug body. Snap it in place.

Repeat the above procedure for the other end of the patch cord.

Test the completed cable assembly to ensure that it meets your performance requirements.