

Pocket Toner® NX8 Cable Kit

Test voice, data and video cables for open and short circuits, continuity and voltage

Quickly and easily test coax and telephone cables for continuity, AC and DC voltage, shorts, opens and 50-75 Ω termination—8x faster, all in a single, versatile kit.

Simply place each of the numbered ID caps on the remote ends of the cables to test then connect the main unit to the other end of the test cables one at a time. If there is continuity, the green LED on the ID cap will light and the main unit will show the ID cap's number (1-8) on its digital display. In addition, the audible indicator in the main unit will emit a short tone. PTNX8 also tests for the presence of both AC and DC voltages from 6v-52v.

Features

- Test cables 8x faster with 8 ID caps—with LED to indicate continuity
- Low-voltage circuit protection (6v-52v) in main unit, toner unit and ID caps
- Eight-segment LED displays five different test results
- Main unit “beeps” when line condition changes
- Bi-gender toner unit w/removable Speed 81™ coupler
- Two buzzers to indicate continuity
- Auto shutoff feature extends battery life
- One-year limited warranty

What's in the kit

- Pocket Toner® NX8
- 8 ID caps
- Alligator clips adapter
- F-female coupler (F-81)
- F-male coupler (F-71)
- F-female coupler (Speed 81™)
- F-male push-on adapter
- AAA battery
- Deluxe case with belt clip



**8x
Faster**

Test Results Display

	Blinking [-] indicates an open circuit
	Blinking [S] indicates a short
	Solid [C] indicates continuity with either a 50-75 ohm ID cap or the toner unit
	A solid matching number indicates continuity with one of the 8 ID caps
	Blinking [~] indicates AC voltage (>6 volts)
	Solid [~] indicates DC voltage (>6 volts)



**Cable
Professional**



**Cable &
Telephone**



Voice

PN# PTNX8-CABLE



For more information: www.flukenetworks.com/PT